


HIRSCHMANN MAS60 DIN P/N FR: 889779

PIN	WIRE COLOR	SIGNAL
1	YELLOW	+5V
2	RED	/RMT_RED_SWITCH
3	WHITE	FOOT_PEDAL
4	BLUE	/RMT_BLUE_SWITCH
5	BLACK+GREEN	GND
6		NC
SHELL	SHIELD	GND

SHELL PIN SOLDER SIDE  
CABLE LENGHT: 2m



TO LASER HARP

FOOT SWITCH WIRING DIAGRAM  
(\*) = OPTIONAL TO ADJUST LED BRIGHTNESS

BLUE SWITCH	WHITE SWITCH	RED SWITCH	GREEN SWITCH	RMT BLUE SWITCH	FOOT PEDAL	RMT RED SWITCH
OFF	OFF	OFF	OFF	HIGH	HIGH	HIGH
ON	OFF	OFF	OFF	LOW	HIGH	HIGH
OFF	ON	OFF	OFF	HIGH	LOW	HIGH
OFF	OFF	ON	OFF	HIGH	HIGH	LOW
OFF	OFF	OFF	ON	LOW	HIGH	LOW
ON	ON	OFF	OFF	LOW	LOW	HIGH
OFF	ON	ON	OFF	HIGH	LOW	LOW
OFF	ON	OFF	ON	LOW	LOW	LOW

[HTTP://WWW.HARPELASER.COM](http://WWW.HARPELASER.COM)

Copyright 2010 under the Creative Commons Attribution Share-Alike

<http://creativecommons.org>

ALL SMD CAPACITORS ARE X7R UNLESS OTHERWISE SPECIFIED

LOGO2  
LEAD FREE

(\*) = NOT MOUNTED

MORISSEAU Franck  
A.K.A. GENESIS



RS = RADIOSPARES  
FR = FARNELL  
DK = DIGIKEY

SCHEM: foot_switch_adapter	
NOM: LASER HARP	
REF.: FOOT SWITCH ADAPTER	REV.: A
DATE: 23/12/2013 14:58:45	
PAGE: 1/1 A4H-GENESIS	

REPRODUCTION PARTIELLE OU TOTALE  
SOUmise A MON ACCORD PREALABLE